

## **Acom 1000 160-6m linear amplifier best value in an amateur hf amplifier**

### **£2,799.95**



## **DESCRIPTION**

The ACOM 1000 HF Linear Amplifier is the world's best value in an amateur HF amplifier. The ACOM 1000 gives you a comfortable 1000 watts output on all amateur bands from 160 through 6 meters. Easy to operate. The plate-load True Resistance Indicator (TRI) is a powerful tuning aid that, together with the automatically controlled input attenuation, helps the operator to quickly and precisely match antennas (5-10 seconds typically). The auto-operate function (when enabled) maintains the amplifier in OPERATE mode for you, thus saving manual operations and time. No antenna tuners, The amplifier will perform the functions of an antenna tuner for VSWR up to 3:1, thus enabling you to change antennas faster and use them over a wider frequency range (saving tuning time). User-friendly, An amplifier that is both user-friendly, and looks after itself. It is designed to safely withstand up to 300W reflected power, up to 100 milliseconds duration of drive spikes, drive RF "tails" after a PTT or KEY release, operator's inadvertent tuning errors, etc. It would also not cease to function with a "soft" AC line and would deliver more than half power at only 75% of the nominal mains voltage. Withstands up to 10 milliseconds (down to zero) voltage drops, and up to +15% line voltage spikes - important particularly when used at field days, Expeditions, etc. LCD comment display, Text messages, 12 parameters, and strip peak-reading PEP meter displayed on a dot-matrix, back-lighted LCD. LED indicators are provided for OPERATE, attenuation-on, and ON/OFF conditions. Easy maintenance Signatures of the amplifier's internal status are stored in non-volatile memory for the 7 most recent auto-protection trips. This information is used for diagnostics. Virtually silent QSK, The input bypassing and the vacuum antenna relays are very quiet even in CW mode due to their special mounting. Broadband input matching Resulting in a very good load to the transceiver over the entire spectrum 1.8-54MHz. Single 4CX800A (GU74B) A Svetlana high-performance ceramic-metal tetrode with plate dissipation of 800W is employed (forced air cooling, grid-driven). Tube protection, Permanent monitoring and protection of plate and grid voltages and currents and the exhaust temperature. Frequency Coverage: All amateur bands 1.8-54MHz; extensions and/or changes on request. Power Output: 1000W PEP or continuous carrier, no mode limit. Inter modulation Distortion: Better than 35dB below rated output. Hum and noise: Better than 40dB below rated output. Harmonic Output Suppression: 1.8-29.7MHz - better than

50dB below-rated output; -50-54MHz - better than 66dB below rated output. Input and Output Impedances: - nominal value: 50 Ohm unbalanced, UHF (SO239) type connectors; - input circuit: broadband, VSWR less than 1.3:1, 1.8-54MHz continuously (no tunings, no switching); - bypass path VSWR less than 1.1:1, 1.8-54MHz continuously; - output matching capability: better than VSWR 3:1 or greater at reduced output levels. RF Gain: 12.5dB typically, frequency response less than 1dB (50 to 60W drive power for rated output). Primary Power: 170-264V (200, 210, 220, 230 & 240 nominal taps, 100, 110 & 120V taps on request, +10%-15%tol.), 50-60Hz, single phase, 2000VA consumption at rated output. Complies with CE safety and EMC requirements, as well as FCC regulations (6,10 & 12m bands lock provided). Size & Weight (operating): - W x D x H: 422x355x182mm, 22kg. - (16.6x14x7.2 inches, 48.5lbs) Operating environments: - temperature range: 0...+50 degs. Celsius; - humidity: up to 75% @ +35 degs. Celsius. - height: up to 3000m above sea level without output deterioration.